

Allworx[®] Px 6/2 Expander Installation Guide



No part of this publication may be reproduced, stored in a retrieval system, or transmitted, in any form or by any means, electronic, mechanical, photocopy, recording, or otherwise without the prior written permission of Allworx.

© 2008 Allworx, a wholly owned subsidiary of PAETEC. All rights reserved. Allworx is a registered trademark of Allworx Corp. All other names may be trademarks or registered trademarks of their respective owners.

Table of Contents

i

1	Installation Overview	1
2	Procuring and Installing the Internet Call Access Feature Key	2
3	Chassis Views	4
4	Mechanical	6
4.1	Tabletop or Shelf Placement.....	6
4.2	Wall Mount	6
5	Electrical.....	8
5.1	Chassis Ground	8
5.2	Power-Up Sequence	8
6	Diagnostic Port	9
7	Port Expander Configuration	10
7.1	Configuring the Port Expander Password	10
7.2	Local Connection	11
7.3	Remote Connection	12
8	Telephone Line Connection	14
9	Data Network Connection	15
10	Physical and Environmental Specifications.....	16
11	Regulatory Notices	17
11.1	FCC Part 68	17
11.2	Industry Canada.....	17
11.3	Radio and Television Interference	18
12	Wall Mount Template	20

1 Installation Overview

Note: Use of the Allworx Px 6/2 Expander requires connection to an Allworx 6x, 10x, or 24x server. The server must be equipped with the Internet Call Access Feature Key. Procure the key before beginning installation at the customer site. Steps for procuring the key are included in Section 2, Procuring and Installing the Internet Call Access Feature Key.

Installation of the Allworx Px 6/2 Expander involves the following steps:

1. Procurement and Installation of Internet Call Access Feature Key on Allworx server.
2. Unpacking
3. Mechanical Installation
4. Electrical Installation
5. Port Expander Configuration
6. Telephone Line Connection
7. Network Connection

Each of these steps will be described in the following sections.

2 Procuring and Installing the Internet Call Access Feature Key

Note: Use of the Allworx Px 6/2 Expander requires connection to an Allworx 6x, 10x, or 24x server. The server must be running Release 6.9 and must have the Internet Call Access Feature Key installed. Obtain the key using the following procedure:

1. Update the server to Release 6.9, if it has not already been upgraded.
2. Submit a request for the Internet Call Access key to allworxorders@allworx.com or fax to 585-421-3853.

Request must include:

- Name of requestor
 - Name of Company
 - Phone number
 - Email address
 - Px 6/2 Expander serial number
 - Associated server serial number (e.g. 6x)
3. Once Customer Care validates the request, the key will be sent to the requestor (and to any additional e-mail address provided by the requestor) with the key information.
 4. If the server has access to the Internet, on the server Admin Maintenance / Feature Keys page, click the Install button. If the server does not have access to the Internet, copy and past the key into the Key field on the server Admin Maintenance / Feature Keys page.

allworx Px 6/2 Expander Installation Guide

Unpacking

Open the box and carefully unpack it. Save all shipping and packaging materials. Verify all items against the parts list shown in Table 1. If any items are missing, contact your dealer or Allworx Customer Support at 866-255-9679.

Quantity	Item
1	Allworx Px 6/2 Port Expander
1	Power Adapter (12 VDC @ 1A)
1	Px 6/2 Port Expander Installation Guide
1	Sheet of 4 Rubber Feet

Table 1: Parts List


3 Chassis Views

Figure 1: Front Chassis View



- 1 Power LED – Indicates system start-up activity
- 2 Outside Analog Phone Line LEDs – Indicates status of a particular FXO port
- 3 Inside Analog Extension LEDs – Indicates status of a particular FXS port
- 4 Network LED – Indicates Ethernet link status; flashes for activity

Figure 2: Rear Chassis View



- 5 Diagnostic port
- 6 RJ-45 10BaseT/100BaseTX Auto-Sensing Auto-MDI/MDIX Ethernet port.
- 7 RJ-11 FXS ports for inside extensions (Ports 7-8)
- 8 RJ-11 loop-start FXO for central office connection (Ports 1-6)
- 9 RJ-11 Power Fail analog phone connector
- 10 Ground connecting screw
- 11 5.5 x 2.1 mm power jack. Input 12 VDC @ 1A, center positive

4 Mechanical

4.1 Tabletop or Shelf Placement

To install the Allworx Px 6/2 on a tabletop or shelf:

1. Remove the four rubber feet from the packaging.
5. Turn over the chassis and notice the triangle on each corner (2 large triangles in front, 2 smaller in back).
6. Remove the paper backing from each rubber foot and place one foot in each triangle.

4.2 Wall Mount


To mount the Allworx Px 6/2 on ½" drywall:

1. Verify that there is sufficient clearance around the Port Expander's front and rear panels to allow power, network, and telephony connections.
2. Use self-drilling drywall anchors rated for at least 20 lbs with screws that are either #6 or #8. Locate two anchors that will support the upper end of the unit using the template included in Section 12, Wall Mount Template. Install the anchors per the anchor manufacturer's recommendation. Install the mounting screws into the anchors leaving approximately 1/8" between the bottom of the screw head and the wall.
3. Slide unit onto mounting screws. Adjust screw height if necessary to insure a snug fit against the wall.


Caution: The Allworx Port Expander must be securely mounted to the wall to avoid equipment damage or personal injury.

Note: The unit must be mounted with the front facing forward, not up or down (see Figure 3).

Figure 3: Wall Mount Orientation



Correct Orientation



Wrong Orientation

5 Electrical

5.1 Chassis Ground

Warning: Failure to follow these steps may result in equipment damage, personal injury, and void the product warranty.

To help prevent electrical shock, the separate, protective earthing terminal located next to the power jack on the rear panel (See Figure 2 item 10) must be permanently connected to earth using 18 AWG wire or larger.

5.2 Power-Up Sequence

Connect the unit's Network port to an Allworx server LAN. Then connect the AC power adapter. The Port Expander will automatically begin to power up. As it progresses through the power up sequence, the front panel Power LED will flash green. If a network connection has been made and when the unit is ready, the Power LED will shine steady green.

If no network connection has been made prior to when the unit is powered on, the Power LED will change from flashing green to solid amber. Solid amber indicates that the unit is in Configuration Mode.

6 Diagnostic Port

The Diagnostic connector (See Figure 2, Item 5) is a serial port. Should Allworx Customer Support instruct you to capture diagnostic data, connect a null modem serial cable from the Diagnostic connector to the serial port on a PC. Configure the PC port in accordance with the following table:


Baud	9600
Data Bits	8
Parity	None
Stop Bits	1
Flow Control	None

Table 2: Serial Port Configuration

7 Port Expander Configuration

Much like an Allworx phone, the Port Expander gets its configuration information and software updates from the Allworx server. Therefore, the Network port of the Allworx Px 6/2 must be attached either directly or remotely to an Allworx server. This is usually done by connecting to the server LAN through a network switch. . Up to three Port Expanders can be connected to a given server. The diagram below depicts three Port Expanders connected on a server LAN. When connected this way, the Port Expanders require no manual configuration steps.

Figure 4, Connection Diagram



7.1 Configuring the Port Expander Password

Although connecting the Port Expander normally does not require any manual configuration, the need to configure the Port Expander's settings may arise in the future. Such situations can be made more convenient by setting the Port Expander's password during installation.

For security reasons, Allworx Px 6/2 Port Expanders do not have a default password. A site-specific password must be created and entered using the Port Expander's Configuration web page. Do this using the following procedure:

1. If the Port Expander has already been powered on, disconnect power.
2. If a cable is plugged into the Network port, disconnect it.
3. Set up the PC's network interface to obtain an IP address automatically (using DHCP).
4. Apply power to the Port Expander.
5. Wait until the power and port LEDs light solid amber (about 45 seconds). Connect the PC's network port to the Port Expander's Network port with a standard RJ-45 category 5 Ethernet cable.

6. Verify that the PC has an IP address on the 192.168.2.xxx network.

You may need to release and renew the PC's IP address using the ipconfig command in a command window to get an address from the Port Expander.

7. Open a web browser on the PC and enter <http://192.168.2.254> into the browser's address field.

The Port Expander's Configuration screen is displayed.

8. Scroll to the New Password field. Enter the site's new Port Expander administrator password. Re-enter the password in the Confirm Password field.

9. Click Update

The Port Expander's Update Result screen is displayed.

10. Disconnect the network cable from the Port Expander's Network port. Connect the Port Expander to the system using the procedure in either Section 7.2, Local Connection or Section 7.3, Remote Connection.
11. Save the password for future reference. If the password is lost or forgotten, it can be reset by repeating this procedure and entering a new password.

7.2 Local Connection

When properly connected to the server LAN, the Allworx Px 6/2 will be configured automatically. This should require no manual steps, although it is recommended that the password be set in accordance with the procedure, above. To ensure the automatic configuration is successful, perform the following steps:

1. If the Port Expander has already been powered on, disconnect power.
2. Connect the Network port of the Port Expander to the LAN of the Allworx server per the diagram above using a standard RJ-45 category 5 Ethernet cable.
3. Apply power to the Port Expander.
4. Observe the Power LED. During power up, it will flash green. When the LED stops flashing and shines solid green, the Port Expander has received any software updates and has been configured. This may take as long as five (5) minutes. It is now ready for CO lines and analog phones to be connected to its FXO and FXS ports.
5. If the Power LED does not shine solid green within five (5) minutes. Unplug and re-plug the Port Expander's power adapter.
6. Activate the FXO and FXS ports through the Web Admin page on the Allworx Server. Refer to the Allworx *System Administrator's Guide*, Release 6.9 or higher for information on configuring the ports.

7.3 Remote Connection

Allworx Px 6/2 Port Expanders can be configured to run at sites that are remote to the Allworx server. Much like with a remote Allworx phone, this requires manual configuration of the Port Expander. The Boot Server IP (the Allworx Server's IP) and the server's Plug and Play Secret Key must be entered within the Port Expander's configuration interface. In addition, forwarding of ports through intervening firewalls may be required. See the *Allworx System Administrator's Guide, Release 6.9* for instructions for configuring firewalls.

Caution: Correct routing of 911 emergency calls for analog handsets attached to remote Allworx Port Expanders cannot be guaranteed. Do not use the Px's FXS ports for handsets from which placing 911 calls may be attempted.

Caution: If the network connection between the Port Expander and the Allworx server is interrupted, regular use of the Port Expander's FXO and FXS ports will not be possible. The only option for placing calls through a Port Expander that does not have a functional network connection to its Allworx server is to plug an analog phone into the Power Fail port. Calls placed using this phone will be routed to the CO line connected to FXO port 1. No other ports will be functional.

To configure the Boot Server IP and Plug and Play Secret Key, perform the following steps:

1. Access the Port Expander's Configuration screen by performing Steps 1 through 7 of the procedure in Section 7.1, Configuring the Port Expander Password.
2. Navigate to the Boot Server IP Address field. Enter the IP address of the Allworx Server to which the Port Expander will be associated.
3. Navigate to the Plug and Play Secret Key field. Enter the Allworx Server's Secret Key. To determine the server's Secret Key, see the *Allworx System Administrator's Guide, Release 6.9* for instructions.
4. Re-enter the key in the Confirm Plug and Play Secret Key field.
5. If the Port Expander's administrator password has not been set, scroll to the New Password field. Create a site-specific password and enter it into the New Password field. Re-enter the password in the Confirm Password field.

6. Click Update

The Port Expander's Update Result screen is displayed.

7. Click Restart
8. Connect the Network port of the Port Expander to the site's network using a standard RJ-45 category 5 Ethernet cable.

Note: A network path to the Allworx Server must be available.

9. Observe the Power LED. During power up, it will flash green. When the LED stops flashing and shines solid green, the Port Expander has received any software updates, and has been fully configured. This

allworx Px 6/2 Expander Installation Guide

may take as long as five (5) minutes. It is now ready for CO lines and analog phones to be connected to its FXO and FXS ports.

10. If the Power LED does not shine solid green within five (5) minutes. Unplug and re-plug the Port Expander's power adapter.
11. If you have entered a new password, save it for future reference. If the password is lost or forgotten, it can be reset by repeating the procedure in Section 7.1, Configuring the Port Expander Password and entering a new password.
12. Activate the FXO and FXS ports through the Web Admin page on the Allworx Server. Refer to the *Allworx System Administrator's Guide for Release 6.9* or higher for information on configuring the ports.

8 Telephone Line Connection

Caution: To reduce the risk of fire, use only 26 AWG (or larger) UL listed or CSA certified telecommunications line cord.

The Port Expander's analog phone connections can be used to connect Central Office (CO) lines or telephone handsets. The following table describes the ports:

RJ-11 Ports	Type	Description
1-6	FXO (loop-start)	Used to connect to Central Office (CO) lines
7-8	FXS	Analog telephone handsets

Table 3: Analog Telephony Ports

It is recommended that the ports be connected as follows:

- CO Lines: Begin with port 1 and move up.
- Telephone Handsets: Begin with port 8 and move down.

The Power Fail Phone port may be used to connect an analog phone device that is operational in the event that the Port Expander loses power, if it loses its network connection to the Allworx server, or if some other hardware failure occurs. When in this condition, calls using an analog phone connected to the Power Fail Phone port will be routed to the first outside phone line port (port 1).

Surge protection is provided internally on all telephony interfaces.

Under normal operation of the unit, the port LEDs will appear as listed, below.

Port LED Indicator	Port (1-8) State
Off	Normal Idle
Green Solid	Off Hook
Green Fast Blink	Ringing
Alternating Red/Amber	No loop current detected on last off hook attempt (FXO only)

Table 4: Analog Port LED Definitions

9 Data Network Connection

The Network port is 10BaseT/100BaseTX auto-sensing and auto-MDI/MDIX port.

Once the Port Expander is powered up and in normal mode, the Network LED indicates the state of the Network link, as shown below.

Color	State	Description
Green	Off	No link: the network is not connected
	On	Link: the network is successfully connected
	Blinking	Activity: data is being transmitted or received

Table 5: Network Port LED Definitions

10 Physical and Environmental Specifications

Dimensions (W x H x D)	12.1 x 1.9 x 7.6 inches (30.8 x 4.8 x 19.3 cm)
Weight (Base Model)	3 lbs
Power	DC 12V, 1 Amp.
Temperature	0° ~ 40° C
Humidity	15% ~ 90% RH, Non-condensing

Table 6: Physical and Environmental Specifications

11 Regulatory Notices

11.1 FCC Part 68

This equipment complies with Part 68 of FCC rules and the requirements adopted by ACTA. On the backside of this equipment is a label that contains, among other information, a product identifier in the format US:AAAEQ##TXXXX. If requested, provide this number to the telephone company.

A plug and jack used to connect this equipment to the premises wiring and telephone network must comply with the applicable FCC Part 68 rules and requirements adopted by the ACTA. See installation instructions for details.

The REN is used to determine the number of devices that may be connected to a telephone line. Excessive RENs on a telephone line may result in the devices not ringing in response to an incoming call. In most but not all areas, the sum of RENs should not exceed five (5.0). To be certain of the number of devices that may be connected to a line, as determined by the total RENs, contact the local telephone company. For products approved after July 23, 2001, the REN for this product is part of the product identifier that has the format US:AAAEQ##TXXXX. The digits represented by ## are the REN without a decimal point (e.g., 03 is a REN of 0.3). For earlier products, the REN is separately shown on the label.

If this equipment causes harm to the telephone network, the telephone company will notify you in advance that temporary discontinuance of service may be required. But if advance notice isn't practical, the telephone company will notify the customer as soon as possible. Also, you will be advised of your right to file a complaint with the FCC if you believe it is necessary.

The telephone company may make changes in its facilities, equipment, operations or procedures that could affect the operation of the equipment. If this happens, the telephone company will provide advance notice in order for you to make necessary modifications to maintain uninterrupted service.

If trouble is experienced with this equipment, for repair or warranty information, please contact our company. If the equipment is causing harm to the telephone network, the telephone company may request that you disconnect the equipment until the problem is resolved.

11.2 Industry Canada

The Industry Canada label identifies certified equipment. This certification means that the equipment meets telecommunications network protective, operation and safety requirements as prescribed in the appropriate Terminal Equipment Technical Requirements document(s). The Department does not guarantee the equipment will operate to the user's satisfaction. Before installing this equipment, users should ensure that it is permissible to be connected to the facilities of the local telecommunications company. The equipment must also be installed using an acceptable method of connection. The customer should be aware that compliance with the above conditions might not prevent degradation of service in some situations.

Repairs to certified equipment should be coordinated by a representative designated by the supplier. Any repairs or alterations made by the user to this equipment, or equipment malfunctions, may give the telecommunications company cause to request the user to disconnect the equipment.

allworx Px 6/2 Expander Installation Guide

Users should ensure for their own protection that the electrical ground connections of the power utility, telephone lines and internal metallic water pipe system, if present, are connected together. This precaution may be particularly important in rural areas.

Caution: Users should not attempt to make such connections themselves, but should contact the appropriate electric inspection authority, or electrician, as appropriate.

NOTICE: This equipment meets the applicable Industry Canada Terminal Equipment Technical Specifications. This is confirmed by the registration number. The abbreviation, IC, before the registration number signifies that registration was performed based on a Declaration of Conformity indicating that Industry Canada technical specifications were met. It does not imply that Industry Canada approved the equipment.

AVIS: Le présent matériel est conforme aux spécifications techniques d'Industrie Canada applicables au matériel terminal. Cette conformité est confirmée par le numéro d'enregistrement. Le sigle IC, placé devant le numéro d'enregistrement, signifie que l'enregistrement s'est effectué conformément à une déclaration de conformité et indique que les spécifications techniques d'Industrie Canada ont été respectées. Il n'implique pas qu'Industrie Canada a approuvé le matériel.

NOTICE: The Ringer Equivalence Number (REN) for this terminal equipment is 0.1. The REN assigned to each terminal device provides an indication of the maximum number of terminals allowed to be connected to a telephone interface. The termination on an interface may consist of any combination of devices subject only to the requirement that the sum of the Ringer Equivalence Numbers of all the devices does not exceed 5.

AVIS : L'indice d'équivalence de la sonnerie (IES) du présent matériel est de 0.1. L'IES assigné à chaque dispositif terminal indique le nombre maximal de terminaux qui peuvent être raccordés à une interface téléphonique. La terminaison d'une interface peut consister en une combinaison quelconque de dispositifs, à la seule condition que la somme d'indices d'équivalence de la sonnerie de tous les dispositifs n'excède pas 5.

11.3 Radio and Television Interference

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. There is no guarantee, however, that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and the receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

You may also find helpful the following booklet, prepared by the FCC: "How to Identify and Resolve Radio-TV Interference Problems." This booklet is available from the U.S. Government Printing Office, Washington D.C. 20402.

Changes and Modifications not expressly approved by the manufacturer or registrant of this equipment can void your authority to operate this equipment under Federal Communications Commissions rules.

This digital apparatus does not exceed the Class A limits for radio noise emissions from digital apparatus set out in the Radio Interference Regulations of the Canadian Department of Communications.

Le présent appareil numérique n'émet pas de bruits radioélectriques dépassant les limites applicables aux appareils numérique de la class A prescrites dans le Règlement sur le brouillage radioélectrique édicte par le Ministère des Communications du Canada.

12 Wall Mount Template

